HOMESYSTEM

QUICK START GUIDE

Shelly BLU Wall Switch 4 ZB

Battery-powered 4-button wall switch (Bluetooth / Zigbee)

Manufacturer: **Shelly** · Model: **Shelly BLU Wall Switch 4 ZB (SBBT-104CEU)**

PRODUCT IN THE HOMESYSTEM E-SHOP

obchod.homesystem.sk/en/shelly-blu-wall-switch-4-zb-ovladac--bluetooth-zigbee/

This guide belongs to a product purchased at obchod.homesystem.sk. Scan the QR code for up-to-date information, accessories and advice.

A wireless controller without a relay – it does not switch anything itself, it sends commands to Shelly relays or a Zigbee gateway. Each button recognises single, double, triple and long presses – up to 16 actions.

BASIC INFORMATION

Model	SBBT-104CEU (Standalone)
Power supply	1× CR2032 battery, 3 V (included), up to 2 years
Wireless	Bluetooth LE 5 or Zigbee 3.0; encrypted communication
Range	up to 10 m indoors, up to 30 m outdoors
Buttons	4 buttons × 4 press types = 16 actions
Dimensions / weight	46 × 46 × 13 mm / 17 g; ivory
Environment	−20 to 40 °C, 30–70 % RH
Mounting	double-sided tape, screws, switch frame (Legrand, Gira, Merten, Busch-Jaeger, Shelly) or portable

SAFETY INSTRUCTIONS

CAUTION

- Keep the coin-cell battery out of reach of children – swallowing it can cause serious injury.
- Use only a CR2032 battery and insert it with correct polarity. Protect the switch from water.

BUTTONS

Press any button 4×	Bluetooth pairing for 1 minute (LED flashes once every 2 s)
Press any button 5×	Zigbee pairing for 1 minute (LED flashes twice every 2 s)
Hold 30 s right after inserting the battery	factory reset
Single, double, triple and long press	actions you set in the app or on the gateway

FIRST START – BLUETOOTH (SHELLY)

1. Prepare a gateway: Shelly BLU Gateway or a Shelly Plus, Pro, Gen3 or Gen4 relay.
2. In the Shelly Smart Control app add a new BLU device.
3. Press any button on the switch 4 times and complete pairing in the app.
4. Assign actions to the buttons (e.g. light on, blinds, scene).

FIRST START – ZIGBEE

1. Allow devices to join on your Zigbee gateway or coordinator (e.g. Home Assistant with Zigbee2MQTT).
2. Press any button on the switch 5 times.
3. Once joined, set up automations for the individual buttons on the gateway.

> **NOTE**
> - The switch is paired with one network at a time – Bluetooth or Zigbee; you can change the protocol later. As a battery device it does not extend the Zigbee network.

Disposal: A product marked with the crossed-out wheeled bin symbol must not be disposed of with household waste. Take it to a WEEE collection point or return it to the retailer when buying a new device. Dispose of batteries separately at a battery collection point.
Important: this quick guide in English was prepared by HomeSystem s.r.o. for customers of the obchod.homesystem.sk e-shop based on the manufacturer's documentation. In case of discrepancies, the manufacturer's original manual prevails: https://kb.shelly.cloud/__attachments/a_bc761e8d0e31ce6c649297a271c646967b7eaf46fd716c1b1333ebd4f3f2a301/Shelly%20BLU%20Wall%20Switch%204%20ZB%20multilingual%20printed%20user%20and%20safety%20guide%20standalone.pdf
Product: obchod.homesystem.sk/en/shelly-blu-wall-switch-4-zb-ovladac--bluetooth-zigbee/ · Version: 11/2026
Need advice? obchod.homesystem.sk · +421 948 213 492